

# Hytera S1 Mini



**MTECH**  
brentwood  
communications

## Quick Start Guide

Action	What to Do
<b>Power On / Off</b>	Press and hold the Power Button until the LED lights up or fades.
<b>Adjust Volume</b>	Tap the Volume Up or Volume Down Buttons to adjust the volume of the device.
<b>Change Channel</b>	Rotate the Channel Selector knob or use programmable keys via app.
<b>Transmit (Talk)</b>	Hold the PTT (Push-to-Talk) Button and speak 2.5 to 5 cm from the mic.
<b>Receive Calls</b>	When you release the PTT button, the radio switches to receiving mode.



## Additional Features

<b>Headset Audio</b>	The earpiece supplied must be plugged into the audio jack for private communications.
<b>Battery Charge</b>	Charge via USB C port - orange LED will flash during charging and will turn to a steady green LED to indicate full charge. Battery will last up to 18 hrs, (100 hrs when on standby).
<b>LED Indicators</b>	Show charging status, indicate in transmit with flashing red light, receiving will show a flashing green light, and can also be used when scanning, and to demonstrate power-on status.
<b>Coloured Labels</b>	Comes with three coloured labels to visually distinguish radios.
<b>Radio Clone &amp; Channel Copy</b>	Use key combinations or Bluetooth app to clone settings from one device to another—streamlines fleet setup.
<b>Voice Notifications</b>	Channel and battery info can be heard audibly.

## Handy Tips

	<b>Transmit Instructions</b> Hold the radio 2.5 - 5cm from your mouth when speaking. Make sure to speak into the microphone.		<b>Label Your Radio</b> Use the coloured stickers that come with each radio to label your radio. Easily identify radios by users or teams.		<b>Radio Care</b> Avoid exposure to moisture or extreme temperatures. Keep your radio clean with a soft, damp cloth.
---	--	---	--	---	--

